

# Fluke 80K-15 High Voltage Probe



## Nøkkelfunksjoner

- **Voltage range:** 0 to 15kV DC or peak AC, 10kV rms AC
- **Basic accuracy:** DC +/- 2% 60Hz: +/- 5%
- **Division ratio:** 1000:1
- **Safety standards:** IEC 1010-2-031:1993, Type B, 40 kV DC or peak AC, 28kV rms AC, Overvoltage Category I (voltage derived from limited energy transformer).
- **Input resistance:** 1000 Megohm
- **Required meter input resistance:** 10 Megohm

## Produktoversikt: Fluke 80K-15 High Voltage Probe

The 80K-15 is a high voltage probe designed to extend the voltage measuring capability of an AC/DC voltmeter to 15,000 volts peak AC or DC Overvoltage Category I. This means the probe can only be used to make measurements on energy limited circuits within equipment. Examples include high voltage within televisions or photocopy machines. DO NOT use this probe to measure high voltages on power distribution systems. The probe provides high accuracy when used with a voltmeter having 10 Megohm input impedance.

## Modeller



**Fluke 80k 15**

**Fluke.** *Keeping your world up and running.®*

**Fluke Norge AS**  
Postboks 383  
1411 Kolbotn  
Tlf: 800 18 227  
E-mail: [cs.no@fluke.com](mailto:cs.no@fluke.com)  
[www.fluke.no](http://www.fluke.no)

©2024 Fluke Corporation. Med enerett.  
Informasjonen kan endres uten varsel. Vi tar  
forbehold om trykkfeil.  
11/2024

**Endring av dette dokumentet er ikke tillatt uten  
skriftlig tillatelse fra Fluke Corporation.**